Assembly Instructions for cable gland: 501/414 Exd IIC Gb / Exe IIC Gb / Extb IIIC Db

15mm minimum

thread length

1

2

Operating temperature range -60°C +100°C

4

5



Certification Details

Gland Type: 501/414 Exd IIC Gb / Exe IIC Gb / Extb IIIC Db Baseefa06ATEX0056X 🚯 II 2 GD IP66 (IECEx BAS06.0013X EAC Ex No: TC RU C-GB.ГБ05.В.00750 IEx No: 14.0272X c CSA us No: 1015065 Class 1 Zone 1 AExd IIC, AExe II Zone 21 AExtD Class 1 Div 2 ABCD, Class II Div 2 Groups EFG, Class III

Backnut Running C

- Running Coupler Sub-Assembly
- Spring Clip

Seal

5. Entry

3. 4.

IMPORTANT: Prior to installation, it may be necessary to release conduit from its clamping mechanism to allow sufficient movement.

Cable Preparation

00



A

Pull sufficient length 'I' of cable through conduit/cable gland to suit equipment. Screw backnut ^① onto pre-threaded conduit/cable gland and tighten with spanner/wrench.

Gland Preparation

Conduit or

Cable Gland

В

Pass the cable through the entry (5) and seal (4) which may have previously been fitted into the equipment.



с

Locate the running coupler ⁽²⁾ onto the entry ⁽⁵⁾ and tighten using a wrench/spanner until resistance is felt between the seal and cable, then turn the running coupler through a further half to one full turn to complete the inner seal, ensuring that entry ⁽⁵⁾ is prevented from turning and backnut ⁽¹⁾ remains tight on the conduit. This procedure compresses the seal ⁽⁴⁾ into contact with the cable outer sheath.

Connection Solutions

Hawke International is a division of Hubbell Ltd. Registered No. 669157 in England. Registered Office: Cannon Place, 78 Cannon Street, London EC4N 6AF.

www.ehawke.com

UK Office Oxford Street West, T Ashton-Under-Lyne, Lancashire. OL7 0NA. UK

Sales: +44 (0) 161 830 6698 Technical: +44 (0) 161 830 6697 Fax: +44 (0) 161 830 6648 E-mail: sales@ehawke.com

CONDUIT CABLE GLAND SELECTION TABLE												
Size Ref.	Male Entry		Female Entry Thread Size		Outer Sheath				ed	_	Hexagon	
	Thread Size				Standard		Alternative)th Jth	Dimensions	
	Metric	NPT	Metric	NPT	Seal		Seal (S)		mpress	Maximum Length		
					Min.	Max.	Min.	Max.	Compress Length	M	Across Flats	Across Corners
Os	M20*	1⁄2"	M20	#	3.2	8.0			54.5	69	24.0	26.5
0	M20 [•]	1⁄2"	M20	#	6.5	11.9			54.5	69	24.0	26.5
Α	M20	1⁄2" - 3⁄4"	M20	#	10.0	14.3	9.5	13.4	56.4	69	30.0	32.5
В	M25	³ ⁄4" - 1"	M25	#	12.5	20.2	9.5	15.4	48.2	61	36.0	39.5
С	M32	1" - 1¼"	M32	#	19.0	26.5	15.5	21.2	61.6	77	46.0	50.5
C2	M40	1" - 1¼"	M40	#	25.0	32.5	22.0	28.0	64.6	77	46.0	60.6
D	M50	1" - 1¼"	M50	#	31.5	44.4/42.3	27.5	34.8	83.2	77	46.0	70.8
Е	M63	1" - 1¼"	M63	#	42.5	56.3/54.3	39.0	46.5	83.2	77	46.0	88.0
F	M75	1" - 1¼"	M75	#	54.5	68.2/65.3	49.5	58.3	86.4	77	46.0	104.0

 Sizes Os and O are available with an M16 thread size. If M16 entry is used on O size Cable Glands the maximum cable inner sheath diameter is limited to 10.9mm.

Thread sizes specified with order

ACCESSORIES:

Before cable gland assembly or stripping of the cable gland assembly, consideration should be given to any cable gland accessories that may be required, such as: -

- Shroud, to offer additional corrosion protection.
- Locknut, to secure cable glands into position.
- Sealing washer, to offer additional ingress protection of the enclosure at the cable gland entry.
- Earthtag, to provide an external armour/braid bonding point.
- Serrated washer, to dampen any vibrations that may loosen the locknut or cable gland assembly.

- SCHEDULE OF LIMITATIONS Baseefa ATEX / IECEx:
- These cable gland types are only suitable for use with fixed apparatus, the cable for which must be effectively clamped and cleated elsewhere.
- 2. This cable gland has an operating temperature range of -60°C to $+100^\circ\text{C}.$
- 3. A seal must be formed between the equipment and the cable gland to maintain the appropriate degree of protection against ingress of dust, solid objects and water.

NOTES - c CSA us:

- 1. The cable used must have extruded sealing (solid polymeric) completely surrounding the "core" (insulation and conductor), allowing for no holes or ventilation through the inner jacket or along the cores.
- 2. The 501/4** series cable gland connectors, when used in Class 1 Division 2 Classified areas, are not suitable to be interfaced with an explosion proof enclosure containing arcing and sparking devices, unless installed in conjunction with an approved explosion proof sealing fitting.
- 3. Class 1 Division 2 suitable for use with conduits and cable glands for use in Marine Shipboard applications only according to CSA Standard 245 and IEEE45 / IEC 600092-353 Standards, or certified equivalent, for use on Shipboards and Offshore Rigs / Platforms only.
- 4. Must comply with Canadian Electrical Code and National Electric Code requirements for threaded entries.
- 5. For Exe applications, a sealing washer or thread sealant may be required between the enclosure and the gland to maintain the IP rating of the enclosure.
- 6. When used with unarmoured or braided cables the glands are only suitable for use with fixed apparatus and the cable must be effectively clamped and cleated elsewhere.
- 7. This cable gland may only be installed when temperature is above -5°C. After completion of the installation, the assembly is then suitable for -60°C to +100°C.



A. Tindall **Technical Manager**